


# XSeries - XSeries V

WITH VIDEO VERIFICATION

**X412** | 4 - 12 zones  
**X412V** | split double, triple EOL  
 + 2 zones for each keypad\* (max 4 zones)



Clamps removable  
(X824-X864)



CMS  
multiformat



Voice  
managing

**X824** | 8 - 24 zones  
**X824V** | split double, triple EOL  
 + 2 zones for each keypad\* (max 8 zones)



**X864** | 8 - 64 zones  
**X864V** | double, triple EOL



PSTN on board | IP / IP Wi-Fi module

GPRS/3G/4G module

Hybrid system (wired and wireless input)

Voice support

BUS line (4 wires) RS485



iOS/Android APP  
**AMCPlus**



iOS/Android APP  
**AMCPlus+**  
VIDEO VERIFICATION





Settable by PC



The **XSeries / XSeries V** are security control panels for building protection; hybrid system (wired and wireless input). EN 50131, Grade 2, Class 2 approved. The control panels have **audio support on board** and are equipped of 4/8 zones, expandable to 16/64. It is possible to obtain more zones by double and triple EOL split line (X412-X412V-X824-X824V).

XSeries / XSeries V are able to notify one or more situations of ALARM, ROBBERY, TAMPERING and TROUBLE with different carriers:

- **PSTN LINE on board** (voice call, Contact ID, SIA fsk, etc.)
- **GPRS/3G/4G module** (voice call, SMS, Contact ID, DC09 IP protocol for Contact ID and SIA IP)
- **IP / IP Wi-Fi module** (DC09 IP protocol for Contact ID and SIA IP)

The panels can be controlled by App (iOS/Android) with IP module and/or GPRS/3G/4G module.

The programming can be made with keypad and/or PC software.

The programming with software can be made remotely with IP module and/or GPRS/3G/4G module.

Technical Features	X 412	X 412 V	X 824	X 824 V	X 864	X 864 V
<b>ZONES</b>	4 - 12 zones split double, triple EOL + 2 zones for each keypad* (max 4 zones)		8 - 24 zones split double, triple EOL + 2 zones for each keypad* (max 8 zones)		8 - 64 zones double, triple EOL	
<b>WIRELESS ZONES</b>	64 zones		64 zones		64 zones	
<b>OUTPUTS</b>	5 on board - expandable to 8 (with expansions or keypads)		5 on board - expandable to 8 (with expansions or keypads)		5 on board - expandable to 17 (with expansions or keypads)	
<b>USER CODE</b>	32		32		64	
<b>AREAS</b>	4		4		8	
<b>GROUPS</b>	4		4		4	
<b>KEYPADS</b>	4		4		8	
<b>TAG READER</b>	4		4		8	
<b>LOG EVENTS</b>	1000		1000		1000	
<b>PHONE NUMBERS</b>	8 for SMS and private calls + 8 for CMS		8 for SMS and private calls + 8 for CMS		8 for SMS and private calls + 8 for CMS	
<b>CARRIERS</b>	PSTN on board, GPRS/3G module, IP module	PSTN on board, GPRS/3G/4G module, IP module	PSTN on board, GPRS/3G module, IP module	PSTN on board, GPRS/3G/4G module, IP module	PSTN on board, GPRS/3G module, IP module	PSTN on board, GPRS/3G/4G module, IP module
<b>REMOTE MANAGEMENT</b>	by App (iOS - Android)		by App (iOS - Android)		by App (iOS - Android)	
<b>REMOTE PROGRAMMING</b>	by PC software		by PC software		by PC software	
<b>MULTI-USER MANAGEMENT VIA APP</b>	-	YES	-	YES	-	YES
<b>VIDEO VERIFICATION</b>	-	YES	-	YES	-	YES
<b>TIMERS</b>	4 per day week		4 per day week		8 per day week	

### Accessories

<b>IP-1</b> - IP module	YES	YES	YES	YES	YES	YES
<b>IP-1 W</b> - IP module Wi-Fi	-	YES	-	YES	-	YES
<b>X GPRS</b> - GPRS module	YES	YES	YES	YES	YES	YES
<b>X 3E / X 3A / X 3J</b> - 3G module	YES	YES	YES	YES	YES	YES
<b>X 4W</b> - 4G module	-	YES	-	YES	-	YES
<b>KX-AL</b> - remote power supply	-	YES	-	YES	-	YES
<b>IFV 800</b> - wireless PIR detector with integrated Wi-Fi camera	-	YES	-	YES	-	YES

\* Keypads with zones are Unika, K-lcd Blue, K-lcd Blue Tag, K-lcd Light Plus